



150W 12V/24V Outdoor Constant Voltage LED driver

Product Offering



Order part number: OD-AD-150W-12V-UN-F-20 OD-AD-150W-24V-UN-F-20

Product Description:


- Constant Current + Constant voltage output
- Active power factor control
- Universal input voltage range
- Full potting with robust housing (IP67 rating)

Feature:

- High efficiency; PF > 0.9
- Reinforced insulation from input and output
- Cooling by free air convection
- Fully protected: Short circuit, input voltage surge, overvoltage protection, over-temperature protection

Technical Data

Rated supply voltage, AC	220-240 Vac, 50/60Hz
AC Voltage range, AC	100-264 Vac, 50/60Hz
Survive input range (for 30mins)	170-305 Vac, 50/60Hz
Rated current @230Vac	<0.9A
Leakage current @240Vac	<0.5mA@240Vac
Max. input power	170W
Typ. efficiency (at 230V 50Hz, full load)	Тур. 90%
Inrush current	<80A (T-width @100µs)
Typ. λ (at 230 V 50Hz, Full load)	>0.9
Typ. λ (at 230 V 50Hz, Min. load)	>0.9
Output rated power	15W
Ambient temperature ta	-15 +60 °C
Max. Casing temperature tc	90 °C
Size (mm)	228x68x39
Weight	765g



Primary Cable		Secondary Cable		
L	N	FG	+V	-V
brown	blue	Green/ yellow	red	black

Standard comply

EN55015;	EN61000-3-2;	EN61000-3-3;	EN61547;
EN61347-1;	EN61347-2-13;	SELV	

Specific Technical Data

	I			Г
Order Part number	Max. output current	Constant output voltage ⁽¹⁾	Constant current region ⁽¹⁾	Ripple voltage
OD-AD-150W-12V-UN-F-65	12500mA	12Vdc	6 - 12Vdc	<150mV
OD-AD-150W-24V-UN-F-65	6250mA	24Vdc	12-24Vdc	<150mV

Remark: (1) For detail specification, please refer to the "Technical Information".

Notes: - Specifications may vary without notice - Always consult local electrical codes - Parameters are measured at rated output, rated load and at an ambient temperature of 25°C - Parameters are measured at rated output, rated load and at an ambient temperature of 25°C - Expect slight variation including component tolerance, setup tolerance, line regulation and load regulation. - Power supplies should always be stress tested and tested for EMC within specific fixture - Where grounding/earthling is not indicated, avoid grounding/earthling or contact with grounded/earthed metal enclosures - Performance with dimmers, where supported, may vary depending on dimmer model